

93.3 MM



**porodo** | CHOOSE THE BEST



## 4000mAh PORTABLE CAR WASH MACHINE

**18000RPM**  
Brush Motor

**4000MAH**  
Battery

**10-13 BAR**  
Pump Pressure

190 MM



Powerfull  
Motor



Build In  
Filter



Long Pipe  
Nozzle



Foam  
Port

### Main Function

1. Wireless portable car washing machine
2. Power 200W, Peak 240W
3. Battery high power rate 18650 2000mAh\*10pcs rechargeable battery ( 5pcs in series, two groups in parallel, the label shows: 21V, 4000mAh), Built-in protection IC, overcharge, overdischarge, overcurrent protection
4. 7 series brush motor, 18000RPM 21V
5. High pressure pump, preset pressure 10-13 BAR (1.45mm Aperture)
6. Ultra long rang 6-8 Meters
7. Charging input DC 3.5
8. When fully charged, it can be used for 40-50mins
9. Carbon brush life above 500 hours
10. Water Rate: 4L/Mins



### Specifications

Portable Car Wash Machine  
Battery: 4000mAh, 84WH  
Type: LI-ion Battery  
Motor Power: 21V

PD-PCWM2-BKOG

[www.porodo.net](http://www.porodo.net)

[/porodo](#)

[/myporodo](#)